

Substitute Specification and Claims
Filed 9-29-06

Fail-Safe circuit for gas valves

This application claims priority to PCT/EP2005/002855,
filed on March 17, 2005, which claims priority to
5 DE102004016764.8 filed on April 1, 2004.

Technical Field

The invention relates to a fail-safe circuit for gas
valves.

10

Background

Control devices for gas valves must be fail-safe. If the
state of the control device is undefined, then it must be
guaranteed that in this undefined state a gas valve
15 controlled by the control device does not open. If, for
example, a microprocessor is used as the control device
for gas valves, then the use of a fail-safe circuit may
help ensure that the whole arrangement is fail-safe.

20 Recently, piezo-operated gas valves have been used,
particularly in low-voltage applications such as water
heaters without a mains connection. The piezo-operated
gas valves are often controlled by a control device in
the form of a microprocessor. In such low-voltage
25 applications, the supply voltage is often approximately 3
volts, which can be provided by a battery. However, a
voltage of typically at least 150 volts is required to
open the piezo-operated gas valves. Accordingly, a fail-
safe circuit is often desirable for low-voltage
30 applications of this kind, which, on the one hand,
provides an output voltage of at least 150 volts to open
the piezo-operated gas valves from a low supply voltage
of approximately 3 volts, and, on the other, only
generates the output voltage required to open the piezo-
35 operated gas valves if the control device, often in the
form of a microprocessor, is in a defined state to open
the gas valves.

Substitute Specification and Claims
Filed 9-29-06

Summary

According to one illustrative embodiment the present invention, a fail-safe circuit includes at least one
5 input that can be connected to a control device and at least one output that can be connected to a gas valve, where the fail-safe circuit only supplies an output voltage that is required to open a gas valve to the, or to each output, if an input signal containing at least
10 two different, successive frequency signals is applied by the control device to an input of the fail-safe circuit.

In some cases, a fail-safe circuit is created for gas valves, in particular for piezo-operated gas valves,
15 which, on the one hand, is able to provide an output voltage of more than 150 volts that is required to open piezo-operated gas valves from a supply voltage of only approximately 3 volts, and, on the other, only provides this output voltage required to open the piezo-operated
20 gas valves if the control device is in a defined state to open the gas valves. One illustrative fail-safe circuit may be characterized by a simple design and can be implemented cost-effectively.

25 According to one illustrative embodiment, the fail-safe circuit may include a charging circuit and a voltage transformer circuit, but this is not required. The charging circuit may have at least one capacitor, where the charging circuit charges the one or more capacitor in
30 the charging circuit when a first frequency signal is applied or is present in the input signal. On the other hand, when a second frequency signal is applied or is present, the one or more capacitors in the charging circuit discharge. In some cases, the voltage transformer
35 circuit produces an output voltage that is required to open the gas valve from a supply voltage when the second frequency signal is applied or is present in the input

Substitute Specification and Claims
Filed 9-29-06

signal. The voltage transformer circuit may have at least one capacitor, which charges when the second frequency signal is present in the input signal, and which discharges when the first frequency signal is present in the input signal, and hence maintains the output voltage required to open the gas valve more or less unchanged for a period of time.

Brief Description

The invention may be more completely understood in consideration of the following detailed description of an illustrative embodiment of the present invention in connection with the accompanying drawings, without being restricted to this or other illustrative embodiment, in which:

Fig. 1 shows a circuit diagram of a fail-safe circuit for gas valves according to one illustrative embodiment of the present invention.

Description

An illustrative embodiment of the present invention is described in greater detail below with reference to Fig. 1.

Fig. 1 shows a fail-safe circuit 10 for gas valves according to one illustrative embodiment, in particular for low-voltage applications. Possible examples of such low-voltage applications are water heaters without a mains connection in which piezo-operated gas valves are used. In such low voltage applications, a supply voltage is typically provided from a battery or from a generator integrated within the water circulation, the supply voltage in such applications is often about 3 volts. In Fig. 1 the supply voltage is identified with V_{BAT} .

Substitute Specification and Claims
Filed 9-29-06

In the illustrative embodiment of Figure 1, the fail-safe circuit 10 has an input to which a control device sometimes in the form of a microprocessor can be
5 connected, and two outputs 12 and 13, from which a supply voltage $\pm V_{OUT}$ is output for a gas valve. Depending on the signal from the control device, which is applied to the input 11 of the illustrative fail-safe circuit 10 of Fig. 1, the circuit may generate the output voltage V_{OUT}
10 that is necessary to open the gas valve using the supply voltage V_{BAT} , which is approximately 3 volts, namely only when an input signal containing at least two different successive frequency signals is supplied by the control device to the input 11 of the fail-safe circuit 10.

15 The illustrative fail-safe circuit 10 of Fig. 1 has a charging circuit 14 and a voltage transformer circuit 15. The charging circuit 14 and the voltage transformer circuit 15 contain the components enclosed by chain-dotted lines in Fig. 1.
20

The charging circuit 14 of the illustrative fail-safe circuit 10 includes a capacitor 16, where two diodes 17 and 18 are connected in parallel with the capacitor 16. A
25 resistor 19, which is connected to the input 11 of the fail-safe circuit 10 via a capacitor 20, is connected between the two diodes 17 and 18.

As can be seen in the illustrative embodiment of Fig. 1,
30 a transistor 22 is connected to the input 11 of the fail-safe circuit 10 via a resistor 21, the transistor 22 being designed as a bipolar transistor, namely as an NPN transistor in the illustrative embodiment. The base of the transistor 22 is connected to the input 11 of the
35 fail-safe circuit 10 by means of the resistor 21. Connected to the capacitor 16 of the charging circuit 14 is a further resistor 23, which in turn is linked to the

Substitute Specification and Claims
Filed 9-29-06

collector of the transistor 22 and the base of a
transistor 24 of the voltage transformer circuit 15. The
transistor 24 is in turn designed as a bipolar
transistor, namely as an NPN transistor in the
5 illustrative embodiment.

In the illustrative embodiment of Fig. 1, the emitters of
the two transistors 22 and 24 are connected together. As
well as the transistor 24 already mentioned, the base of
10 which is connected on the one hand to the collector of
the transistor 22 and, on the other, by means of the
resistor 23 to the capacitor 16 of the charging circuit
14, the voltage transformer circuit 15 furthermore
contains a comparator 25, a coil 26, a diode 27, a
15 capacitor 28, a resistor 29 and a further transistor 30.
The transistor 30 is designed as a field effect
transistor or a MOSFET transistor in the illustrative
embodiment.

20 As can be seen from Fig. 1, the coil 26 is connected on
the one hand to the supply voltage V_{BAT} and, on the other,
to the so-called drain of the transistor 30, which is
designed as a self-blocking field effect transistor in
the illustrative embodiment. An anode of the diode 27 is
25 connected between the coil 26 and the drain of the MOSFET
transistor 30, whereas the cathode of the diode 27 is
connected to the output 12. The source of the MOSFET
transistor 30 is shown connected to the output 13, while
the capacitor 28 of the voltage transformer circuit 15 is
30 shown connected between the outputs 12 and 13 of the
fail-safe circuit 10. As can also be seen from Fig. 1,
the output of the comparator 25 connects to the gate of
the MOSFET transistor 30 while the input of the same is
connected to the collector of the bipolar transistor 25.
35 Furthermore, the collector of the transistor 24 is
connected by means of the resistor 29 to the coil 26 and
thus to the supply voltage V_{BAT} .

Substitute Specification and Claims
Filed 9-29-06

As already mentioned, the fail-safe circuit 10 may only generate an output voltage of over 150 volts that is required to open the gas valve at the outputs 12, 13 if a
5 signal containing at least two different successive frequency signals is provided by the control device at the input 11 of the fail-safe circuit 10. In this case, a defined operating state of the control device for opening the gas valve exists.

10 In the illustrative embodiment, the input signal may contain two frequency signals, namely a first frequency signal with a frequency of about 500 kHz and a second frequency signal with a frequency of about 10 kHz, which
15 are present or are applied successively in the signal provided by the control device in such a way that a time period of about 30 milliseconds with the first frequency signal of about 500 kHz is respectively followed by a time period of about 100 milliseconds with the second
20 frequency signal of about 10 kHz.

The illustrative fail-safe circuit 10 of Fig. 1 may work in such a way that when the first frequency signal of about 500 kHz is applied or is present at input 11, the
25 charging circuit 14 charges the capacitor 16 of the same. While the second frequency signal of about 10 kHz is applied to the input 11, the capacitor 16 of the charging circuit is not charged but rather a discharge of the capacitor 16 takes place via the resistor 23 and the base
30 of the transistor 24. The transistor 24 of the voltage transformer circuit 15 is then conductive if a current flows to its base due to the discharge of the capacitor 16.

35 During the time period for which the first frequency signal of about 500 kHz is applied to the input 11, a high output voltage that is required to open the gas

Substitute Specification and Claims
Filed 9-29-06

valve cannot be generated by the voltage transformer circuit 15 due to the high losses, in particular in the coil 26 and in the MOSFET transistor 30 of the voltage transformer circuit 15. Rather, this high output voltage is only generated when the second frequency signal with a frequency of about 10 kHz is applied to the input 11. When the second frequency signal of about 10 kHz is applied to the input 11, an output voltage V_{OUT} of more than 150 volts that is required to open the piezo-operated gas valve is generated from the supply voltage V_{BAT} by the voltage transformer circuit 15, and the capacitor 28 of the voltage transformer circuit 15 is charged.

If a time period of about 100 milliseconds, in which the second frequency signal with a frequency of about 10 kHz is applied, is followed by a time period of about 30 milliseconds with the first frequency signal with a frequency of about 500 kHz, then the capacitor 28 of the voltage transformer circuit 15 discharges and essentially maintains the output voltage of more than 150 volts that is required to open the gas valve. The capacitor 28 discharges via the high resistance of the gas valve during the time period in which the first frequency signal with the frequency of about 500 kHz is applied.

The specific design of the circuit described above is incumbent upon the person skilled in the art addressed here. In the particularly preferred exemplary embodiment in which an output voltage V_{OUT} of about 250 volts is to be provided for opening the gas valve from the supply voltage V_{BAT} of about 3 volts, the capacitance of the capacitor 28 is preferably 1 μF , the capacitance of the capacitor 16 is about 10 μF and the capacitance of the capacitor 20 is about 220 pF. The resistance of the gas valve connected to the outputs 12 and 13 can be assumed to be 10 $M\Omega$, the resistor 21 is preferably chosen to be 1

Substitute Specification and Claims
Filed 9-29-06

M Ω , the resistor 19 to be 1 k Ω and the resistor 29 to be
10 k Ω . The resistor 23 preferably has a value of 22 k Ω .
The coil 26 preferably has an inductance of 1 mH. With
these values, the discharge time of the capacitor 28 is
5 about 10 seconds from which it immediately follows that
an output voltage that is required to open the gas valve
can also be provided at the outputs 12 and 13 during the
time period of 30 milliseconds in which the first
frequency signal of about 500 kHz is applied to the input
10 11.

Substitute Specification and Claims
Filed 9-29-06

List of references

	10	Fail-safe circuit
5	11	Input
	12	Output
	13	Output
	14	Charging circuit
	15	Voltage transformer circuit
10	16	Capacitor
	17	Diode
	18	Diode
	19	Resistor
	20	Capacitor
15	21	Resistor
	22	Transistor
	23	Resistor
	24	Transistor
	25	Comparator
20	26	Coil
	27	Diode
	28	Capacitor
	29	Resistor
	30	Transistor